Presence detector P46LR, DALI-2, secondary - BMS, 32-37 m, IP54, for surface mounting, white

353-752021

This presence detector is a DALI-2 secondary and BMS detector that extends the detection range of a DALI master detector or as part of a BMS system. It is designed for surface mounting and has an IP54 protection degree. If the secondary detector is connected to a DALI bus with a DALI master, it will start communicating with this master without further commissioning. If it is connected to a DALI bus or a BMS system, the detector needs to be commissioned with the BMS software. The detector's settings can be modified using the Niko detector tool app and 2-way Bluetooth[®] communication between a smartphone and the detector or using the BMS software. Finishing colour: white

Compatible master detectors: 353-650321, 353-651321, 353-651421, 353-652321, 353-652421, 353-750321, 353-751321, 353-751421, 353-752321, 353-752421, 353-852411


This article is protected by at least one patent (application). For more info on patents, see www. niko.eu/innovation.

- Surface mounting
- Easy installation thanks to the direct connection to the DALI bus
- Communication with the master or BMS system via the DALI bus
- Power supply via the DALI bus
- Quick cabling using screwless and easily accessible plug-in terminals
- User-friendly app for settings (iOS/Android) or BMS software
- 2-way Bluetooth[®] communication ensures quick modification of settings and live feedback in the app
- Fitted with three PIR segments, each covering 120°
- Pre-configured functions:
- adjustable PIR sensitivity (4 levels) in 3 x 120°
- one or more PIR segments can be disabled
- event log keeps track of recent changes
- Settings and configuration can be locked with a PIN code
- IP54 protection degree



4 year warranty

Detection range



Н	А	В	С	D
	Walking	Across	Towards	Presence
₽	no.		nn 1	ĉ
<u> </u>		·///>	۱) ^۲ ۱	
2.5 m	ø 32 m	ø 28 m	ø10 m	ø 8 m
3.0 m	ø 37 m	ø 30 m	ø 8 m	ø 4 m

Measured according to EN/IEC63180






Technical data

Article number	353-752021		
Compatible master detectors	353-650321, 353-651321, 353-651421, 353-652321, 353-652421,		
	353-750321, 353-751321, 353-751421, 353-752321, 353-752421, 353-		
	852411		
Input voltage	via the DALI bus		
Detector output	DALI-2		
Maximum current consumption	28.1 mA		
Nominal current consumption (12 V, 25°C), Bluetooth® enabled	8.1 mA		
Nominal current consumption (12 V, 25°C), Bluetooth® disabled	5 mA		
Maximum MCB rating	16 A (limited by national installation rules)		
Maximum startup time DALI	<1200 ms		
Maximum PIR detection startup time	1 min 10 s		
Light intensity range	0 lux – 10360 lux		
Detection angle	360°		
Detection range (PIR)	ø 37 m from a height of 3 m		
Ambient temperature	-25 - +40 °C		
Mounting method	surface mounting		
Mounting height	2 – 3.5 m		
Colour	white (approximately RAL 9010)		
Dimensions visible (HxWxD)	100 x 100 x 70.7 mm		
Dimensions (HxWxD)	100 x 100 x 70.7 mm		
Maximum range Bluetooth® (free field, depending on the device)	50 m		
Operating frequency	2.4 GHz		
Maximum radio frequency power	-2 dBm		
Protection degree	IP54		
Impact resistance	IK04		
Modification of settings	Niko detector tool app (iOS-Android) and 2-way Bluetooth®		
	communication - BMS software		
Halogen-free	yes		
Marking	CE		

Accessories

Lens cover for P4XLR, M4XLR and M4XHC detectors transparent (5 pieces) 353-999879

Dimensions





Wiring diagram

